


www.marantzpro.com

PHONE: [401] 658.5766



PMD-750 Wireless Camera-Mount System

Key Features:

- Complete 2.4GHz portable wireless system
- Compact, innovative design
- PMD-750R receiver mounts to DSLR camera hot shoe
- PMD-750T beltpack transmitter with robust belt clip
- Receiver can pair to two transmitters for expandability
- System includes lavalier mic, foam & fuzzy windscreens, and receiver output cable
- Simple, easy to use user interface
- Locking 4-pin mini-XLR input and output jacks
- (2) AA battery operation
- PMD-750TA plug-on transmitter available separately
- Additional PMD-750T beltpack transmitter available separately

Overview:

Designed for professional DSLR filmmakers, the PMD-750 Series Camera Mount Wireless System is compact and

Specifications:

- Audio Performance
 - Frequency Spectrum: 2.401 - 2.483 GHz
 - Dynamic Range: > 100 dB
 - THD: < 0.2 %, typical
 - Latency: 4.5 m
 - Operating Range: Up to 100' (31m)
- Beltpack Transmitter
 - Frequency Response: 50 Hz - 18 kHz
 - Maximum Input Level: -20 dB
 - Bias Voltage: 5V (for condenser mics)
 - Input Impedance: 10 kΩ
 - Power: (2) AA alkaline batteries
 - Dimensions (width x depth x height): 2.6" x 4.0" x 1.6" (65 x 102 x 40mm)
 - Weight: 82g
- Receiver
 - Frequency Response: 50 Hz - 18 kHz
 - Pairing Bands: 16 channels
 - Audio Quality: Uncompressed 96 kHz/24-bit
 - Operating Temperature: 14° to 131° F (-10° to 55° C)
 - Maximum Output Level: -12 dB

simple to operate. The lightweight build is perfect for camera and rig-mounting, but rugged enough for daily field use. The PMD-750 system includes everything needed to get up and running...PMD-750T beltpack transmitter, PMD-750R camera-mount receiver, omnidirectional lavalier microphone with two styles of windscreens, and receiver output cable. The system also features locking 4-pin mini-XLR input and output jacks for secure connectivity, robust beltclip on the transmitter, and secure hot shoe mount on the receiver. The user interface is simple to use, and the OLED screens on the components are easily readable outdoors in sunlight. The apex of the feature list is the ability of the PMD-750R receiver to pair with two separate transmitters. The PMD-750TA plug-on transmitter for dynamic or battery-operated condenser wired microphones is available separately. The PMD-750T beltpack transmitter is also available as a separate item, ready to expand the PMD-750's versatility. The system is perfect for any type of DSLR shooting requiring remote microphones, such as interviews, special events, ENG, and corporate trainings.

PMD-750

- Output Impedance: 300 Ω
- Power: (2) AA alkaline batteries
- Dimensions (width x depth x height): 2.6" x 4.0" x 2.2" (65 x 102 x 55mm)
- Weight: 90
- Lavalier Microphone
 - Frequency Response: 20 Hz - 20 kHz
 - Output Impedance: 3 k Ω
 - Pattern: Omnidirectional
 - Type: Electret Condenser
 - Sensitivity: -38 dB, \pm 3 dB
 - Equivalent Noise: 25 dBA
 - Maximum SPL Level: 130 dB
 - Dimensions: Cable length 41.3" (1050mm)
 - Weight: 16g