CRESTRON. DO GUIDE

DM-NVX-350/DM-NVX-351

DigitalMedia[™] 4K60 4:4:4 HDR Network AV Encoder/Decoder

DO Install the Device

The Crestron® DM-NVX-350 and DM-NVX-351 can be mounted onto a flat surface or rack rail.

Mount onto a Flat Surface

Using four mounting screws (not included), mount the device onto a flat surface such as a wall or the underside of a table.

NOTE: Fan ventilation holes are provided on five sides of the device. If the installation necessitates that another object be positioned flush against the ventilation holes on one side of the device, leave a minimum clearance of 2 inches of space on all other sides containing ventilation holes.



Mount onto a Rack Rail

Using two mounting screws (not included), mount the left or right mounting flange of the device onto the front or rear rail of a rack.



DO Check the Box

QTY	ITEM	PART NUM.
1	Cable, USB 2.0, A - B, 6' (1.83 m)	2014966
1	Connector, 4-Pin	2003576
2	Connector, 5-Pin	2003577
1	Power Cord, 5' 10" (1.78 m)	2042043
1	Power Pack, 24 Vdc, 2.5 A, 100-240 Vac	2045873

DO Connect the Device

Connect the device as required for the application.

Front Panel Connections







NOTE: The DM-NVX-350 and DM-NVX-351 can be configured to use either the DEVICE port or the HOST port. Both ports cannot be used simultaneously.



NOTE: The DM-NVX-350 and DM-NVX-351 each provide three LAN (品) ports. Only one LAN port at a time can be used as the primary LAN connection to stream network video:

 LAN ports 1 and 2 are 10BASE-T/100BASE-TX/1000BASE-T. Either LAN port 1 or LAN port 2 can be used as the primary LAN connection, allowing the other port to be used for connection to a local network device or to another DM[®] NVX device. If one of the ports is used as the primary LAN connection, the port requires connection to a 1000BASE-T switch in order to stream network video.

LAN port 1 can be powered by the Crestron DM-PSU-ULTRA-MIDSPAN and other Crestron approved power injectors. Refer to Online Help Answer ID 5791 for additional information.

• LAN port 3 is an SFP port that can connect to a fiber-optic network using the appropriate Crestron SFP-1G transceiver module. LAN port 3 can be used as the primary LAN connection or can be connected to another DM NVX device. Refer to the SFP-1G Series Installation Guide (Doc. 7979) for information about installing Crestron SFP-1G series transceiver modules.

DO Configure the Device

Configure the device using the web interface. To access the web interface, open a web browser and then go to the IP address of the device.

NOTE: By default, the IP address of a DM NVX device is assigned by a DHCP server on the network. If a DHCP server does not exist on the network, the IP address defaults to a link-local address in the 169.254.*xxx*.*xxx* range (refer to RFC 3927 for detailed information about link-local addressing).

To display the IP address on the connected display, press the **SETUP** button on the front panel of the device.

To log in to the web interface, enter the user name and password. The default user name and password are both *admin*.

DO Connect to the Crestron XiO Cloud Service

The Crestron XiO Cloud[™] service allows supported Crestron devices across an enterprise to be managed and configured from one central and secure location in the cloud. Supported devices are preconfigured to connect to the service. Use of the service requires a registered Crestron XiO Cloud account.

To connect the device to the Crestron XiO Cloud service:

- 1. Record the MAC address and serial number that are labeled on the shipping box or rear panel of the device. The MAC address and serial number are required in order to add the device to the Crestron XiO Cloud environment.
- 2. Do either of the following:
 - If you have a Crestron XiO Cloud account, go to <u>https://portal.crestron.io</u> to access the Crestron XiO Cloud service.
 - If you do not have a Crestron XiO Cloud account, go to <u>www.crestron.com/xiocloud</u> to register for an account.

For detailed information about using the Crestron XiO Cloud service, refer to the Crestron XiO Cloud Service User Guide (Doc. 8214) at <u>www.crestron.com/manuals</u>.

DO Learn More

DM-NVX-350

Visit the website for additional information and the latest firmware updates. To learn more about this product, use a QR reader application on your mobile device to scan the QR image.

Crestron Electronics

15 Volvo Drive, Rockleigh, NJ 07647 888.CRESTRON | www.crestron.com





HOM

DM-NVX-35



As of the date of manufacture, the product has been tested and found to comply with specifications for CE marking.

This product is Listed to applicable UL[®] Standards and requirements tested by Underwriters Laboratories Inc. Ce produit est homologué selon les normes et les exigences UL applicables par Underwriters Laboratories Inc.

Federal Communications Commission (FCC) Compliance Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

CAUTION: Changes or modifications not expressly approved by the manufacturer responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Industry Canada (IC) Compliance Statement CAN ICES-3(B)/NMB-3(B)



The product is a class 1 laser product. It complies with safety regulations of IEC- 60825-1, FDA 21 CFR 1040.11 and FDA 21 CFR 1040.10.

WARNING: Visible and invisible laser radiation when open. Avoid direct exposure to beam. NOTE: Plug the included dust cap into the optical transceiver when the fiber optic cable is unplugged

The specific patents that cover Crestron products are listed at <u>www.crestron.com/legal/patents</u>.

The product warranty can be found at www.crestron.com/legal/sales-terms-conditions-warranties

Certain Crestron products contain open source software. For specific information, visit www.crestron.com/legal/open-source-software.

Crestron, the Crestron logo, Crestron XiO Cloud, and DigitalMedia are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. HDMI and the HDMI logo are either trademarks or registered trademarks of HDMI Licensing LLC in the United States and/or other countries. UL and the UL logo are either trademarks or registered trademarks of Underwriters Laboratories, Inc. in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography.

This document was written by the Technical Publications department at Crestron.

©2018 Crestron Electronics, Inc.

