



ECA-70MIXAMP-1-60

70V, 100V and 4-Ohm Capable

Supports 70V and 100V, as well as low impedance 4-ohm systems. With a beefy 60 Watts of power, it handles large rooms and multiple speakers with ease.

Multiple Source Inputs

Total of five inputs allows up to three microphones and two analog stereo sources for background music. An integrated mixer blends microphones with any one of the music audio sources – perfect for background music and paging applications.

Variable Mic Inputs with Audio Ducking

XLR, 1/4" and RCA inputs make this mixer ideal for paging or emergency applications, while the front panel 1/4" jack allows for automatic audio ducking when in use.

Front Panel Controls

Volume, Bass, Treble, Source Input and individual mic level controls are easily accessible via the front panel.

Flexible Output Options

Variable unbalanced Mix Out makes system expansion easy to add a second amplifier for more power or additional zones.

Specifications

Power Rating (Watts / Channel)	60 Watts / 1 Channel / 4 Ohms, 50V, 70V, 100V
Power Consumption	120w
Operating Voltage	120V, 60Hz
Number of Channels	1
Construction (Digital / Analog)	Analog
Size	3.75" H x 16.9" W x 12.9" D (Chassis Only, with feet)
	3.5" H x 19.1" W x 12.9" D (Rack Mounted)
Rack Spacing (1U, 2U, 3U)	2U
Weight	18 lbs.
Ratings / Certifications	UL E330247, CE, RoHS

5-Year Limited Warranty

This Episode[®] Commercial Amplifier has a 5-Year Limited Warranty. This warranty includes parts and labor repairs on all components found to be defective in material or workmanship under normal conditions of use. This warranty shall not apply to products which have been abused, modified or disassembled. Products to be repaired under this warranty must be returned to SnapAV or a designated service center with prior notification and an assigned return authorization number