

A2.1 NEW VERSION! AMPLIFICATION SIMPLIFIED

390W 3-CHANNEL (1-SUB, 2-SATS) AMPLIFIER



A

Designed for the stand-alone system in a guest room or bedroom where you desire premium L/R & Subwoofer sound. This may include a soundbar with an in-wall subwoofer.

B

Ready your workstation for a high-end media experience requiring rich L/R & Subwoofer sound.

C

Perfect for the close proximity landscape system using both L/R & Subwoofer speakers.

From the family of quality James Loudspeaker amplifiers we bring you the A2.1.

Designed and engineered by James Loudspeaker, we leveraged our decades of sound engineering experience to build what might be the simplest, most smartly designed amp in the industry. Designed for the stand-alone system located in a guestroom; to complement a high-end multi-media desktop system; and or even for use with close-proximity outdoor systems, the A2.1 fits a number of applications.

New Features

- Remote Control
- Digital Inputs
- Remote IR Receiver
- 12V Trigger
- Selectable Subsonic Filter
- Selectable Input Sensitivity



James
LOUDSPEAKER™
535 Airpark Road, Napa, CA 94558
Ph: 707.265.6343
www.jamesloudspeaker.com

Channels	3 (Left, Right & Sub)
Inputs	Left/right RCA - Analog (Blue LED) Coaxial RCA - Digital (Green LED) Optical S/PIDF - Digital (Purple LED) Switchable via remote or rear push button
Input Sensitivity	0.2V or 0.775V (Switchable on rear)
Sat Crossover Range	40Hz-150Hz (12dB/octave)
Sub Crossover Range	40Hz-150Hz (12dB/octave)
Sub Volume Level	+/-12dB ref to sat level
12V Trigger Input	Min 4VDC required
Subsonic Filter	30Hz/50Hz (Switchable on rear)
IR Input	On rear
USB A Connector	Supplies +5V to optional peripherals
USB B Connector	For factory use only
Bass Phase Switch	0 or 180 deg
Bass Boost	+4dB at 45Hz
Signal Auto Sense	20 minutes

Sub Power Output	170W @ 4 ohms 70W @ 8 ohms
Sat Power Output	110W @ 2 ohms 65W @ 4 ohms 40W @ 8 ohms
Frequency Response	20Hz-20kHz +/- 0.2dB
Distortion	0.1% max THD @ 1W
Size W x H x D	19" x 1.75" x 10" (w/rack ears) 483mm x 44.5mm x 254mm (w/rack ears)
Weight	7.5 lbs (3.4 kg)
Power Requirements	Switchable 120V/240V 50Hz/60Hz 530W max
Standby Power	<0.5W
Supplied Accessories	Remote control 10ft (3m) IR receiver (+adhesive) 6ft (2m) dual RCA to mini phone plug audio cable IEC power cable 4 self adhesive rubber feet