



ECA-70MIXAMP-1-120

### 50V, 70V, 100V and 4-Ohm Capable

Supports 50V, 70V and 100V, as well as low impedance 4-ohm systems. With a beefy 120 Watts of power, it handles large rooms and multiple speakers with ease.

### Multiple Source Inputs

Total of eight inputs allows up to four microphones and four analog stereo sources for background music. An integrated mixer blends microphones with any one of the music audio sources – perfect for background music and paging applications.

### Priority Mic Inputs with Audio “Ducking”

Balanced XLR microphone inputs feature independent priority modes that enable audio “ducking”, automatically attenuating the music when the priority microphone(s) are being used.

### Front Panel Controls

Volume, Bass, Treble, Source Input and individual mic level controls are easily accessible via the front panel.

### Flexible Output Options

Balanced line output allows addition of second amplifier, as well as fixed record output and preamp loop output/ amp input.

### Specifications

Power Rating (Watts / Channel)	120 Watts / 1 Channel / 4 Ohms, 50V, 70V, 100V
Power Consumption	160w
Operating Voltage	120V, 60Hz
Number of Channels	1
Construction (Digital / Analog)	Analog
Size	3.75" H x 16.9" W x 13.9" D (Chassis Only, with feet)
	3.5" H x 19.1" W x 13.9" D (Rack Mounted)
Rack Spacing (1U, 2U, 3U)	2U
Weight	23 lbs.
Ratings / Certifications	UL E330247, CE, RoHS

### 5-Year Limited Warranty

*This Episode<sup>®</sup> Commercial Amplifier has a 5-Year Limited Warranty. This warranty includes parts and labor repairs on all components found to be defective in material or workmanship under normal conditions of use. This warranty shall not apply to products which have been abused, modified or disassembled. Products to be repaired under this warranty must be returned to SnapAV or a designated service center with prior notification and an assigned return authorization number*