

GENERAL			
Number of Channels	5	Amplifier Class	Class FD
Maximum Power Output	2000W	Maximum Power Output at 1 ff	-
Maximum Power Output at 2 ff	200W x 4 (A/B), 1200W (SUB)	Maximum Power Output at 4 ff	150W x 4 (A/B), 700W (SUB)
Maximum Power Output - Bridged at 4 ff	400W x 2 (A/B)	Nominal Power (RMS) Output at 1 ff	-
Nominal Power (RMS) Output at 2 ff	100W x4 (A/B), 600W (SUB)	Nominal Power (RMS) Output at 4 ff	75W x 4 (A/B), 350W (SUB)
Nominal Power (RMS) Output - Bridged at 4 ff	200W x 2 (A/B)	Frequency Response	A/B CH: 10Hz ~ 50kHz (+0dB, -3dB) / SUB CH: 10Hz ~ 500Hz (+0dB, -3dB)
Total Harmonic Distortion (THD)	A/B CH: <0.05% (1kHz) / SUB CH: <0.05% (100Hz)	Signal-to-Noise (SN) Ratio	> 94dB
Fuse Rating	30A x 3		

SPECIFICATIONS			
RCA Inputs	6-CH	Speaker Level Inputs	<input checked="" type="checkbox"/>
Crossover Type	Adjustable HPF/LPF	Low-Pass Crossover Frequency	40-500 Hz
Low Pass Slope (dB/octave)	-12dB/oct (A/B CH) / -12dB/-24dB (SUB CH)	High-Pass Crossover Frequency	40-500 Hz
High-Pass Slope (dB/octave)	-12dB/oct	Bass Boost Frequency	50Hz
Bass Boost Level	0-18dB	Bass Boost Remote	<input checked="" type="checkbox"/>
Automatic Signal Sensing and Turn-On	<input checked="" type="checkbox"/>	Hi-Volt Input Level Control	200 mV to 6.5 V
Terminal Type	Block	Load Impedance Allowance (Ω)	2 to 4
Bridgeable	<input checked="" type="checkbox"/>	MOSFET Output Selection	<input checked="" type="checkbox"/>
Protection Control System	<input checked="" type="checkbox"/>	Dimensions (WxHxD)(inches)	12.4 x 2 x 7.87
Warranty	1 Year		