


# **CROSLEY**


















---

## FURNITURE












### Record Storage Cube Bookcase CF1325



# PART LIST


<b>A</b> 	<b>B</b> 	<b>C</b> 	<b>D</b> 	<b>E</b> 
Top Panel 1 PC	Left Panel 1 PC	Right Panel 1 PC	Bottom Panel 1 PC	Back Panel 2 PCS
<b>F</b> 	<b>G</b> 	<b>H</b> 	<b>I</b> 	<b>J</b> 
Partition Panel 1 PC	Back Rail 1 PC	Drawer Front Panel 1 PC	Drawer Left Panel 1 PC	Drawer Right Panel 1 PC
<b>K</b> 	<b>L</b> 	<b>M</b> 	<b>N</b> 	<b>O</b> 
Drawer Back Panel 1 PC	Drawer Bottom Panel 1 PC	Upper Fixed Shelf Panel 1 PC	Lower Fixed Shelf Panel 1 PC	Back Slat 1 PC
<b>P</b> 	<b>Q</b> 			
Leg 4 PCS	Center Leg 1 PC			

# HARDWARE LIST

#1		#2		#3		#4		#5	
Ø3*15mm Short Screw		Ø3*30mm Long Screw		Ø7*38mm Screw		Ø5/32"*22mm Round Head Bolt		Ø1/4"*15mm Bolt	
8 PCS (Extra 1)		4 PCS		10 PCS (Extra 2)		2 PCS		2 PCS	
#6		#7		#8		#9		#10	
Ø1/4"*30mm Long Bolt		Ø8*30mm Wood Dowel		350*35*11mm Handle		4mm Allen Wrench		Back Bracket	
16 PCS (Extra 2)		26 PCS (Extra 2)		1 PC		1 PC		8 PCS	
#11									
									
Safety Strap Kit									
1 SET									

## ADDITIONAL TOOLS (Not Provided)


Note: It is not recommended to use power tools during assembly.



Phillips Head Screwdriver

Note: Wood dowels are intended for alignment. Additional clearance between wood dowel and pre-drilled hole is intentional for ease of assembly.


Please do not use tools to assemble this unit unless specifically indicated.




Reference the images above any time the instructions state "lock the hardware" or "insert hardware and pull down to lock".

Be sure to check all hardware is locked when complete.


Step 1. Insert drawer left panel (part I) and drawer right panel (part J) into drawer front panel (part H) pull down to lock. Slide drawer bottom panel (part L) into grooves of assembled unit (parts H, I & J). Attach drawer back panel (part K) to assembled unit (parts I, J & L) using long screws (part #2) and phillips head screwdriver. Attach handle (part #8) to drawer front panel (part H) using round head bolts (part #4) and phillips head screwdriver.





Step 2. Insert lower fixed shelf panel (part N) to partition panel (part F).




Step 3. Attach upper fixed shelf panel (part M) to partition panel (part F) using wood dowels (part #7), screws (part #3) and phillips head screwdriver.




#3  x 2  
#7  x 2


Step 4. Attach panels (parts B & C) and back rail (part G) to panels (parts F, M & N) using wood dowels (part #7) and lock the hardware.




Step 5. Attach bottom panel (part D) to assembled unit (parts B, C, F & G) using wood dowels (part #7), screws (part #3) and phillips head screwdriver.




Step 6. Attach legs (parts P & Q) to bottom panel (part D) using bolts (parts #5 & #6) and allen wrench (part #9).




Step 7. Carefully turn unit upright. Attach back slat (part O) to back rail (part G) using wood dowels (part #7).



Step 8. Insert back panels (part E) into grooves of assembled unit (parts B, C, G & O).




Step 9. Attach top panel (part A) to assembled unit (parts B, C & O) using wood dowels (part #7) and lock the hardware.






Step 10. Slide assembled drawer into place.



Note: To release trigger disconnect levers push one side up and the other down.









Note: It is important to adjust levelers once fully assembled and upright. Extend adjustable leveler until it's firmly in contact with the floor. If relocating, adjust leveler as needed until it's firmly in contact with the floor in new location.

Step 11. Secure back brackets (part #10) at the corner of back panels (part E) using short screws (part #1) and phillips head screwdriver.  
 Important: Safety strap kit (part #11) must be installed to prevent tipping, damage and /or injury.



#1  x 8  
 #10  x 8


#11	A	B	C	D	E
			 D8*3/4"	 D8*1-1/2"	
Safety Strap Kit	Wall Anchor	Washer	Short Screw	Long Screw	Safety Wall Strap
1 SET	1 PC	2 PCS	1 PC	1 PC	1 PC

## SAFETY WALL STRAP INSTALLATION

Note: It is highly recommended to install this safety strap kit to prevent tipping, damage and/or injury.

1. Insert short screw (C) through washer (B) and safety wall strap (E) and attach to top panel (part A) using phillips head screwdriver.
2. Drill a 11/32" hole where you want to secure the unit. The drilled hole will be at the same height as the hole in top panel (part A) where the safety wall strap (E) is attached. Tap wall anchor (A) into the hole.
3. Insert long screw (D) through washer (B) and safety wall strap (E) into wall anchor (A) using phillips head screwdriver.

Note: This item is not intended for clothing storage use.



⚠ WARNING	
	<p>Children have died from furniture tipover. To reduce the risk of furniture tipover:</p> <ul style="list-style-type: none"> <li>• ALWAYS install tipover restraint provided.</li> <li>• NEVER put a TV on this product.</li> <li>• NEVER allow children to stand, climb or hang on drawers, doors, or shelves.</li> <li>• NEVER open more than one drawer at a time.</li> <li>• Place heaviest items in the lowest drawers.</li> </ul>
	<p><i>This is a permanent label. Do not remove!</i></p>