

# SPECIFICATIONS

## INPUTS

Audio Inputs: 7 HDMI, 2 XLR, 6 RCA Phono, 4 Coax SPDIF, 2 Toslink  
Nominal sensitivity: 1V, 2V, 4V (user selectable)  
Input Impedance: 47 k $\Omega$   
Signal to Noise (A-wtd ref 100W) normal/stereo direct: 100 dB/110 dB  
Frequency Response: 20 Hz – 20 kHz  $\pm$  0.2 dB  
Video Inputs: 7 HDMI (HDMI 2.0b / HDCP 2.2)

## OUTPUTS

Preamp Audio Outputs: 16 channels (balanced XLR), 16 channels (unbalanced RCA), 2 channels zone 2 (unbalanced RCA), 1 Toslink  
Nominal output level: 1 Vrms (max. 5 Vrms)  
Output impedance: 560  $\Omega$   
THD+N (20 Hz – 20 kHz): -100dB  
Main Video Outputs: Dual (2) HDMI (eARC support)  
Second Zone Output: 1 HDMI  
Headphone Output: 1 1/4"

## CONTROL

IP Ethernet  
Wifi  
RS232 Serial Control  
12 Volt Trigger Outputs: 2  
IR Receiver Inputs: 2

## GENERAL

Power consumption (standby): <0.5W  
Power consumption (idle, typical): 40W (170 BTU/hour)  
Power consumption (maximum): 50W (170 BTU/hour)

## WEIGHTS & DIMENSIONS

Dimensions (including terminals and feet): 17"W x 16.9"D x 7.3"H (4U)  
Weight: 27.1 lbs. (12.3 kg)

**IN THE BOX:** Maestro X7, HTR-3 remote with 2 x AAA batteries, DAB/FM antenna, 3 x WiFi/Bluetooth antennas, calibration microphone, USB cable, power cord, user manual, warranty