

What's In The Box

SUPPLIED ACCESSORIES

Remote Commander: RMT-AH513U, Batteries for remote commander:
R03 (2 PCS), AC Cord

Weight and Measurements

| | |
|---------------------|----------------------------|
| Bar Speaker (WxHxD) | 35 1/2 x 2 5/8 x 4 in |
| Subwoofer (WxHxD) | 7 5/8 x 15 3/8 x 15 3/4 in |
| Bar speaker | 6 lbs 10 oz |
| Subwoofer | 16 lb 2 oz |

Interfaces

| | |
|-------------------|---|
| Bluetooth | RX/- |
| Bluetooth version | 5.3 |
| HDMI | Number of Input/Output: -/1 (eARC/ARC), eARC, BRAVIA Sync, HDMI CEC |
| USB | USB typeA |

Power

Power Consumption (On Operation) *approx Bar: 30 W, Subwoofer: 20 W

Speaker Layout

Speaker Structure 3.1 ch

Speaker Component

Bar Speaker, Subwoofer

Sound Function

Sound Effect

Night Mode, Voice Mode

Virtual Surround Technology

S-Force PRO, Vertical Surround Engine, Dolby Speaker Virtual

Audio Formats

Optical Input

Dolby Digital, Dolby Dual mono, DTS, LPCM 2ch, LPCM fs:
96kHz/24bit

HDMI eARC

Dolby Digital, Dolby Digital Plus, Dolby TrueHD, Dolby Atmos, Dolby
Dual mono, DTS, DTS HD High Resolution Audio, DTS HD Master
Audio, DTS ES, DTS 96/24, DTS:X, LPCM: 2ch/5.1ch/7.1ch, LPCM fs:
192kHz/24bit

BLUETOOTH (RECEIVER)

AAC, SBC

Amplifier

Number of Channel

3.1 ch