marantz®


NR1510
MARANTZ NR1510 SLIM 5.2CH 4K ULTRA HD AV RECEIVER WITH HEOS BUILT-IN

Experience exceptional audio performance from the slim profile Marantz NR1510 5.2ch 4K Ultra HD AV receiver that drives elevated surround sound and high-fidelity audio from a compact chassis. At half the height of a traditional AV receiver, the NR1510 features the latest in HDMI connectivity and delivers high-resolution surround sound from Dolby TrueHD and DTS-HD Master Audio. Stream music from popular online sources and control the NR1510 with voice control compatibility via Amazon Alexa, Google Assistant and Apple Siri.

Highlights

- Slim profile that's half the height of a traditional AV receiver delivers exceptional performance and the most musical sound
- 5-channel discrete power amplifier, 50W per channel (8-ohm, 20Hz – 20kHz, 0.08% THD)
- 6 HDMI inputs with full HDCP 2.3 support
- Supports Dolby Vision, Hybrid Log-Gamma (HLG), eARC and ALLM for enhanced picture and audio
- 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR10 and BT.2020
- Surround format support for Dolby TrueHD and DTS-HD Master Audio
- ALAC, FLAC and WAV lossless file decoding up to 24-bit/192-kHz for high-resolution listening
- HEOS Built-in for multi-room streaming, music streaming and voice control
- Built-in Wi-Fi with 2.4GHz/5GHz dual band support (dual antenna)
- Supports all major voice control agents and streaming services
- Integrated phono input to directly connect your turntable

because music matters

marantz®

NR1510
MARANTZ NR1510 SLIM 5.2CH 4K ULTRA HD AV RECEIVER WITH HEOS BUILT-IN

FEATURES	NR1710
MULTICHANNEL SURROUND	
DTS HD Master / DTS:X / DTS Neural:X	o / - / -
DTS Virtual:X	-
IMAX Enhanced	-
Dolby TrueHD / Dolby Atmos/Dolby Atmos Height Virtualization	o / - / -
Dolby ProLogic IIz / Dolby Surround	- / -
Auro 3D / Auromatic	- / -
Multichannel Stereo	o
Max Number of Processing (Preamp) Channels	5.1
Audyssey	MultEQ
Audyssey Dynamic EQ / Dynamic Volume	o / o
Compressed Audio Enhancer: MDAX2	o
NETWORK	
HEOS Multi-Room and Streaming / Network Audio Streaming	o / o
Lossy Formats: MP3 / WMA / AAC	o / o / o
Lossless Formats: FLAC / ALAC / WAV	o / o / o
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	o / o / o
DSD Audio Streaming	up to DSD5.6
Gapless Playback	o (FLAC, WAV ,ALAC ,DSD)
AirPlay2 Audio Streaming	o
Internet Radio (Tune In)	o (TuneIn)
Spotify connect / Deezer / TIDAL / Napster / Pandora / SiriusXM	o / o / o / o / o / o
Compatible with Remote APP (iOS/Android)	Marantz 2016 AVR Remote
Ethernet / Wi-Fi	o / o (dual antenna/ dual band)
Bluetooth	o
HDMI	
4K 60Hz 4:4:4 resolution / HDCP 2.3	o / o
eARC (Enhanced Audio Return Channel)	o
Analog to HDMI scaling	-
HDMI to HDMI scaling	-
GUI Overlay on HDMI	o
HDR / HLG / Dolby Vision	o (HDR10) / o / o
3D Signal Pass-Through	o
HDMI Pass-Through in Standby Mode	o
MULTIROOM / CI	
HEOS Multi-Room Integrated	o
HEOS Link Compatibility: IR/ IP	o / o
Multi-Room zones	-
Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog	- / - / - / -
IP Control / RS232 Control / Web Control / App Control	o / - / o / o
Domotz Pro / IHIJI compatible	o / o
INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	3 / 1
Component In / Out	- / -
HDMI In / Out	5+1 / 1

AUDIO	
Analog In / Out	3 / -
Phono (MM) In	o
Digital In: Optical / Coaxial	1 / 1
Multi-Room Out: Analog / Digital	- / -
USB Audio / Made for iPod / Made for iPhone	o / - / -
Multichannel Pre Out	o (2.2) / -
Subwoofer Out	2
7.1 Multichannel Input	-
OTHER	
Speaker Terminal: Gold Plated Screw / Regular Screw	- / o
Speaker A / B	-
Bi-Amp Drive	-
Multi-Room Speaker Terminal	-
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	- / - / - / o / o
OTHERS	
FL Display	1 line
Graphic User Interface - GUI	Hybrid GUI
ISF Certification	-
GUI Languages	3
Setup Assistant	o
Smart Select	o
Firmware Update by Network / USB	o / o
Variable Cross Over	o
Optimized Bass Redirection	o
Bass Sync	-
ECO Mode	o
Auto Power Off	o
Sleep Timer	o
SPECIFICATIONS	
Number of Poweramps	5
Number of Speaker Terminals	5
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)	50 W
Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive)	60 W
Power Output (6 ohm, 1 kHz, 10% 1ch Drive)	100 W
GENERAL	
System Remote Control	RC040SR
Power Consumption in W	180
Power Consumption No-Sound (ECO on / off) in W	-
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions	
Antenna Horizontal: W x D x H (mm)	17.3 x 14.9 x 4.1
Antenna Vertical: W x D x H (mm)	17.3 x 14.9 x 6.9
w/o Antenna: W x D x H (mm)	17.3 x 14.5 x 4.1
Weight (lbs)	18.1
UPC		
NR1510U1B	Black	699927241650

Design and specifications are subject to change by Marantz without notice.

* This feature is not available in all countries.

* All specs can be subject to change.