

PULSE MINI



The PULSE MINI delivers true HiFi to any nook and cranny of your home. Using the same technologies as in the flagship PULSE 2, we've shrunk down the footprint without compromising the performance.

Put a PULSE MINI on any bookshelf, countertop or end table, and hear the difference that 60 Watts of tri-amplified 2.1 sound can bring to any room. Add a few around the house, and turn your whole home into a sound studio tapped into all the music ever recorded. Including an amplified headphone output, analog input and even an IR sensor for seamless integration with your TV audio – now you can finally bring your HD home entertainment system up to a total, true HiFi experience.

An innovative dual acoustic chamber with special DSP equalization merges isolated left and right channels through a shared port on the back, resulting in bass power and clarity that you simply have to hear to believe.

Like all PULSE all-in-one Players, when used in pairs, the PULSE MINI is designed to create a large stereo sound field that will expand the way you think about compact speaker performance.

DIGITAL AMPLIFIER
WIFI + GIGABIT ETHERNET
aptX® BLUETOOTH WIRELESS BUILT-IN
2 x 50mm (2") FULL RANGE DRIVER
1x 89mm (3.5") BASS DRIVER
USB TYPE-A INPUT
OPTICAL & ANALOG INPUTS
HEADPHONE OUTPUT
IR REMOTE LEARNING CAPABILITY
SIMPLE TOUCH-PANEL CONTROLS
BLACK OR WHITE FINISH



PULSE MINI Specifications

Supported Operated Systems: Windows Vista, 7, 8, Apple Macintosh OS X 7-10

Supported File Formats: MP3, AAC, WMA, WMA-L, OGG, FLAC, ALAC, WAV, AIFF

Native Sampling Rates: 32 - 192kHz Bit Depths: 16 - 24

Features:

Play/Pause Button: Touch LED
Volume Control Buttons: Touch LED
Previous/Next Track Buttons: Touch LED

Processor: ARM® Cortex™ -A9, 1 GHz

Distortion: THD+N, 0.030%

Amplification: Digital

Power Output: 60W Tri-Amplified

Speakers: 2 x 50mm (2"), 1 x 89mm (3.5")

Frequency Response: 45Hz - 20kHz

Connections:

Power: Universal bi-pin AC cord input (100 - 240AC)

Ethernet /LAN:Ethernet RJ45, GigEWiFi Built In:802.11 b/g/n WiFiBluetooth Built In:Bluetooth 4.0 with aptXIR optical Built In:IR Sensor Built In - Front panelOptical/Analog Input:Combo - Toslink/3.5mmUSB IN:Type A (Fat32 Formatted)

USB: Type B (mini) for product servicing


Headphone Output: 3.5mm Stereo

Power Consumption (Idle): 14W

Finish: Black/White

Dimensions (Unit):

 $\begin{array}{lll} \text{(W x H x D)} & 335 \, \text{x} \, 172 \, \text{x} \, 155 \text{mm} \\ \text{(W x H x D)} & 13.2 \, \text{x} \, 6.8 \, \text{x} \, 6.1 \, \text{in} \\ \text{Weight:} & 3.6 \text{kg}/7.9 \text{lbs} \\ \end{array}$



13.2" -

Included Accessories:

120V AC Power Cord 230V AC Power Cord Ethernet Cable

Toslink Optical to 3.5mm Mini Adaptor

Safety/Warranty Guide Quick Setup Guide

