

The RX-V475BL 5.1 channel network AV receiver provides convenient functions including MHL (Mobile High-Definition Link), AirPlay® and music streaming services, all controllable through Yamaha's free AV Controller App. Front panel connection and charging for your iPod®/iPhone®/iPad® is provided, as well as wireless capability via optional Wi-Fi or Bluetooth® accessories.



Audio Features

- 5-channel powerful surround sound
115W per Channel (8 ohms, 1 kHz, 0.9 % THD, 1 ch driven)
80W per Channel (8 ohms, 20 Hz-20 kHz, 0.9 % THD, 2 ch driven)
- HD Audio format decoding: Dolby TrueHD and DTS-HD Master Audio;
Dolby Digital Plus and DTS-HD High Resolution Audio
- Full discrete amp configuration
- Burr-Brown 192 kHz/24-bit DACs for all channels
- Direct Mode for high quality sound reproduction
- Low jitter PLL circuitry helps optimize sound imaging
- FLAC or WAV 192kHz/24-bit audio playback

Video Features

- 4K pass-through for next generation super high resolution images
- HDMI (5 in/1 out) with 3D and Auto Return Channel
- Supports Deep Color (10/16-bit), x.v.Color, 24 Hz Refresh Rate and Auto Lip-Sync compensation

Advanced Features

- SCENE buttons with direct power on (BD/DVD, TV, Net and Radio)
- Quick and simple to use
- HDMI CEC powers up compatible TVs and Blu-ray Disc™ players
- Network functions
- AirPlay allows music streaming from Mac, PC, iPod®, iPhone®, iPad®
- AV Controller app for operating various functions from an iPod®, iPhone®, iPad® or Android phones
- Access to: Streaming Services (Pandora)
Music files on PC/PNAS: WAV, MP3, WMA, AAC, FLAC
- DLNA 1.5 certified
- MHL supports full HD video and audio from mobile phones and portable devices

- Front panel USB Digital Connection for iPod®, iPhone® and iPad®
- Charging of iPod®, iPhone® and iPad® via USB when AV Receiver is off
- iPod®/iPhone®/iPad® song titles displayed on the front panel
- Multi language color OSD for improved visibility
- HDMI CEC with versatile control from AV Receiver remote control
- YPAO sound optimization for automatic speaker setup
- Audio input assign capability for HDMI and component video input
- Ability to change HDMI input while in Standby Through mode
- Audio Delay for adjusting Lip-Sync (0-250 ms)
- 40-station preset tuning / Auto preset tuning
- Preset remote unit
- Background Video feature (for Radio only)
- DC Out for optional accessories

Surround Realism

- HD Audio decoding with CINEMA DSP 3D (17 DSP programs)
- Compressed Music Enhancer with CINEMA DSP
- Virtual Presence Speaker Function for CINEMA DSP 3D surround without Front Presence Speakers
- Adaptive DRC (Dynamic Range Control) and Adaptive DSP level
- SILENT CINEMA and Virtual CINEMA DSP

Eco-Friendly Design

- ECO mode operation for about 20%* less power consumption
*Compared to power consumption when ECO mode is off (Yamaha measurement)
- Auto power standby function with variable time setting
- Low standby power consumption of 0.1W