

Eco and energy saving

Power Consumption (Off) *Approx	0.3 W
---------------------------------	-------

Power Consumption (on Standby Mode) *Approx	0.5 W
---	-------

To Standby/Off Mode Activated	Low power mode is selected by setting the power button to ON and the platter stops rotating while it is connected to the mains. This product enters low power mode immediately after rotation of the platter is stopped. Eco and energy saving PROD 1/5/26, 5:02 PM PROD PS-LX3BT Automatic Wireless Turntable Specifications Audio Component Sony Global https://author-sonyglobalsolutions-prd65.adobecqms.net/content/sony/global/en/general/audio/audio-components/products/ps-lx3bt/spec.html?view=
-------------------------------	--

Power Consumption (Network Standby Mode) *Approx	not available
--	---------------

Networked Standby Mode Activated - Terminals	not available
--	---------------

Interface

Other input/output	Bluetooth Transmitter: Supported codecs (SBC, aptX, aptX Adaptive)
--------------------	--

Turntable

ARM Pipe Material	Aluminum Alloy Component
-------------------	--------------------------

Auto Return	Yes
-------------	-----

Auto Start	Yes
------------	-----

Auto Stop	Yes
-----------	-----

Cartridge Type	MM
----------------	----

Drive system	Belt Drive
--------------	------------

Earth Terminal	No
----------------	----

Exchangeable Head Shell	No
GAIN SELECT	Low (-4 dB) / Mid (0 dB) / High (+6 dB)
Line Out (Built-in phono pre amp)	Yes
Phono Output	Yes
Platter	φ296 mm, Aluminum Diecast Alloy Component
Speed	33-1/3, 45 rpm
USB connector	B type, No
Supported Vinyl Record Sizes	7" / 12"
Tracking Force	3.5±0.5 g
Output Level	2.5 mV
Rca Fixed Cable	Yes
Audio Output Jack	No
Phono / Line Selector Switch	Yes

Size & Weight

WEIGHT (kg)	approx. 3.5 kg
Dimension (WxHxD inches)	17 in x 4 5 / 8 in x 14 1 / 2 in
Dimension (WxHxD mm)	430 mm x 117 mm x 366 mm
Weight (pound)	approx. 7 lb 11 1 / 2 oz

General Features

Power Consumption	1.8 W
-------------------	-------

Power Requirement

AC 100-240 V 50 / 60 Hz

AC Adaptor

Yes