

AudioControl®

Making Good Sound Great™

*THE ULTIMATE ZONE AMPLIFIER...
...POWER, DAC AND CONTROL*



Bijou⁶⁰⁰™

HIGH POWER AUDIOPHILE AMPLIFIER
WITH DAC AND PREAMP VOLUME CONTROL

MADE IN USA | 100 WATTS PER CHANNEL AT 8 OHMS | 200 WATTS PER CHANNEL AT 4 OHMS
SELECTABLE DIGITAL & ANALOG INPUTS | CONTROL VIA IR & RS232 |
HIGH PERFORMANCE WOLFSON DAC | ACCUBASS®
COMPACT DESIGN FOR IN-WALL OR RACK MOUNTING

HOME AUDIO

HIGH POWER AUDIOPHILE AMPLIFIER WITH DAC

AudioControl's Bijou 600 is the ultimate zone amplifier that combines a high performance Wolfson DAC with preamp volume control. The Bijou 600 has been designed to be 1U half rack mountable or situated discretely in a room behind a TV or in a wall cavity media case. The Bijou 600 dramatically improves the audio quality across all local audio zones. A perfect companion to streaming audio systems, video displays with digital outputs as well as powering speaker set-ups and all local audio needs. Powerful, audiophile quality, AccuBASS®, multiple digital and analog inputs and outputs all in a compact and versatile chassis.

- High power amplifier at 100 watts per channel into 8 ohms
- Amplifier stable into 4 ohms at 200 watts per channel
- Wolfson DAC for audiophile quality and performance
- Preamp volume control across all channels
- Multiple inputs for digital and analog sources
- Perfect for gaming and portable media
- Ideal for streaming audio sources like SONOS
- 1U ½ rack size ideal for rack mount or TV walls
- AudioControl AccuBASS® to maximize bass response
- Small compact size at just 8.5"W x 8.0"D x 1.75"H

COMPACT LOCAL ZONE AMPLIFIER

NUMBER OF CHANNELS	2
POWER RATING (ALL CHANNELS DRIVEN)	100 WATTS @ 8 OHMS 200 WATTS @ 4 OHMS
MINIMUM SPEAKER LOAD	4 OHMS
DIGITAL INPUTS	2X DIGITAL OPTICAL AND COAX
ANALOG INPUTS	1X STEREO, RCA, 1/8" ADAPTOR
SIGNAL TO NOISE RATIO	>95 dB
TOTAL HARMONIC DISTORTION	0.09%
MINIMUM VOLTAGE TO DRIVE TO FULL POWER	RCA INPUTS - .775 mV
DIGITAL AUDIO INPUTS 2 CHANNEL PCM	COAX - SPDIF 75 OHM OPTICAL - TOSLINK
CROSSOVER	HIGH-PASS, LO-PASS, OR BRIDGED 80 Hz 18 dB/OCTAVE
LINE VOLTAGE	100 - 120 VAC/200-240 VAC SWITCHABLE
POWER CONSUMPTION	TYPICAL LISTENING - 40 WATTS MAXIMUM - 520 WATTS
BASS ADJUSTMENT	ACCUBASS®
WEIGHT	5 POUNDS
FINISH OPTIONS	ESPRESSO BLACK
DIMENSIONS	8.5"W x 8.0"D x 1.75"H
COUNTRY OF ORIGIN	USA
LIMITED WARRANTY	5 YEAR

