



Audio   Portable

## Pocket Radio RFP50

Frequency Range		FM 87 - 108MHz (100kHz step) AM 520 - 1710kHz (10kHz step)
AFC (Automatic Frequency Control)		yes
Tuning		Digital
Tuning LED		yes(Red)
Speaker Size		5.7 cm
Output Power (RMS)		150mW (MAX)
Power Source	Battery	DC 3V (R6/LR6, AA, UM-3) x 2
Battery Life [Approx.]	Speaker	R6: FM 24 H, AM 26 H LR6: FM 64 H, AM 68 H
	Headphone	R6: FM 38 H, AM 38 H LR6: FM 94 H, AM 96 H
Headphone Output (3.5mm)		yes (mini/mono)
Dimensions (W x H x D) [Approx.]		69.5 x 117.4 x 29.7 mm
Weight (without batteries) [Approx.]		111 g
NOTIFICATION	Note	•Specifications are subject to change without notice. Weight and dimensions are approximate.