

Specs

Audio



Four full-range woofers ensure you'll hear the faithful playback of mid-range vocal frequencies plus deep, rich bass.



One tweeter creates a crisp and clear dialogue.



Three passive radiators help move air around inside the compact Sonos Beam and add warm sound to the bass.



Adjustable bass and treble controls let you customize your sound by individual room or groups of rooms.



Five Class-D digital amplifiers perfectly tuned to match the speaker drivers and acoustic architecture.



Five far-field microphone array used for advanced beamforming and multi-channel echo cancellation.



When the microphone LED is on, Alexa is ready for a voice command. When the light is off, the microphone is off.

General



Dimensions - H x W x D
2.70 x 25.625 x 3.94 in. (68.5 x 651 x 100 mm)



Weight
6.2 lbs (2.8 kg)



HDMI ARC
HDMI Cable connects to your TV's HDMI ARC input.



Optical Audio
Optical Audio Adapter to connect to your TV. Allows Sonos Beam to support DOLBY DIGITAL and stereo.



Top-panel features
Capacitive touch controls for volume up/down, previous/next track, play/pause, microphone mute. LED indicates status, mute status and voice feedback.

Power & Networking



Power supply
Auto-switching 100-240 V, 50-60 Hz AC universal input.



Ethernet port
One 10/100 Mbps Ethernet port. Wire directly to your router to operate your Sonos if WiFi is unstable.



WiFi
Connects to your home WiFi network with any 802.11b/g, 2.4 GHz broadcast-capable router for uninterrupted wireless streaming. Connects directly via rear surrounds or Sonos Sub to 5 GHz broadcast.



AirPlay compatible
Works with AirPlay on Apple devices [iOS 11.4 and higher]

Contents



Sonos Beam, power cord, HDMI cable, Optical Audio Adapter, Sonos Beam QuickStart Guide and Legal/Warranty information.