

KW-Z1000W

Monitor

High Definition Monitor

Yes

Screen Size

10.1"W HD Screen

Touch Panel

Capacitive / Bonding

Monitor Touch Control

Yes

Customizable GUI

Yes

Key Illumination Color

Variable

Dimmer

Yes

Multilingual Display

Yes[4]

Wallpaper Capture

Yes

Live Wallpaper

Yes

Media Playback

MP3 Compatible with Tag

USB

WMA Compatible with Tag

USB

WAV Compatible with Tag

USB

AAC Compatible with Tag

USB

FLAC Compatible with Tag

USB(Up to192kHz/24bit)

DSD Compatible with Tag

USB

H.264 Compatible

USB

WMV Compatible

USB

MPEG 1/2 Compatible

USB

MPEG 4 Compatible

USB

AVI/MKV Compatible

USB

JPEG File Playback

USB

PNG File Playback

USB

BMP File Playback

USB

Bluetooth Control

Built-in Bluetooth[1]

Yes (Version 5.0, Wired-Mic included)

Hands Free Call

Yes (HFP1.7 Wideband Speech)

2 Phones Full-Time Connection

Yes

Audio Streaming & Control (A2DP, AVRCP)

Yes

Supported Audio Formats

LDAC / AAC / SBC

5 BT-Audio Connection

Yes

Voice Dialing (voice recognition compatible mobile phone required)

Yes

Phone Book Access Profile (PBAP)

Yes

Alphabetical Search for Phone Book

Yes

Auto Pairing for iPhone/Android

Yes

Wi-Fi Control

Built-in Wi-Fi

Yes

Android Control

Android Auto[2]

Yes (via Wi-Fi or USB)

Mirroring for Android

Yes (via Wi-Fi or HDMI)

Android Music Playback

Yes (via Bluetooth(R))

Pandora Control

Yes (Android Auto / Mirroring)

iHeartRadio Control

Yes (Android Auto / Mirroring)

Spotify Control

Yes (Android Auto / Mirroring)

iPod/iPhone Control

CarPlay[3]

Yes (via Wi-Fi or USB)

Mirroring for iPhone

Yes (via HDMI)

iPod/iPhone Music Playback

Yes (via USB or Bluetooth(R))

Pandora Control

Yes (CarPlay / Mirroring)

iHeartRadio Control

Yes (CarPlay / Mirroring)

Spotify Control

Yes (CarPlay / Mirroring)

USB

USB Port

x 2 (High Speed)

Position

Rear

USB Power Supply

Yes (1.5A High Current Charging)

Drive Change Mode for Mass Storage Class (selectable from internal/external memory)

Yes

Radio Tuner

SiriusXM Ready

Yes *SiriusXM 360L Ready

Radio Broadcast Data System (RBDS)

Yes

Preset Stations

20(FM:15ch, AM:5ch)

Automatic Presetting (Strong Station Sequential Memory)

Yes

FM

Frequency Range

87.9 - 107.9MHz

AM

Frequency Range

530-1,700kHz

Audio

Maximum Power Output (Front & Rear)

50Wx4

Full Bandwidth Power (Front & Rear)

22W x 4 (Full Bandwidth Power, at less than 1% THD)

EQ

Yes (13-Band Graphic EQ)

Preset EQ

Yes (8Preset + 4user)

Bass Boost

Yes

High-Pass Filter/Low-Pass Filter

Yes/Yes

3-Way X'over

Yes

High-Resolution Audio

Yes

K2 Technology

Yes

Space Enhancement

Yes

Sound Response

Yes

Sound Lift

Yes

Volume Link EQ

Yes

Time Alignment

Yes

Dual-Zone Function

Yes

Inputs and Outputs

AV Input

mini jack + RCA Video(AV-IN or CAM4 switchable)

Video Out

RCA

Rear view camera Input

Yes

Front view camera Input

Yes

3rd Camera Input

Yes

Line Output Terminals

3 Pairs (Front + Rear + Subwoofer)

Pre-output Level/Impedance

5.0V / 10k ohms

Subwoofer Output with Level/Frequency Control

Yes

General

iDatalink Maestro Ready

Yes

Remote Control Application

Yes

Back Up Memory

Yes

Face Type

Viewing Angle Adjustment

Yes (0 - 20 degree, default : 0 degree) 4 steps

Wireless Remote Control

Ready (RM-RK258 required)

Steering Remote Control Ready

Yes

Learning Direct OEM Remote

Yes

Dimensions (W x H x D)

Installation Size

7" x 3-15/16" x 6-2/16" (178 x 100 x 155 mm)

Weight

7.28 lbs. (3.25kg)