

episode®

Sound Design.



120 Watt Commercial Amplifier-Mixer



EA-AMP-COMM-1A-120A

## DESCRIPTION

This Episode® Amplifier/Mixer is a high-power, one-channel, commercial audio amplifier that includes all the features needed for any light commercial entertainment and paging systems.

### Multiple Source Inputs

A total of eight inputs allows connections of up to four microphones and four analog stereo sources for background music. An integrated mixer blends the microphones with music from the selected audio sources - perfect for background music and paging applications.

## SPECIFICATIONS

<b>Power Rating (Watts / Channel)</b>	<b>120 Watts / Channel / 4 Ohms, 50V, 70V, 100V</b>
<b>Number of Channels</b>	<b>1</b>
<b>Construction (Digital / Analog)</b>	<b>Analog, Class AB</b>
<b>Size (L x W x D)</b>	<b>17.2" x 3.75" x 14.5"</b>
<b>Rack Spacing (1U, 2U, 3U)</b>	<b>2U</b>
<b>Weight</b>	<b>25 lbs.</b>
<b>Ratings / Certifications (UL, CE, Plenum, FCC)</b>	<b>ETL 4001498, CE, FCC Part 15</b>

### Front Control Options

Volume, Bass, Treble, Source and individual Microphone level controls are accessible via the front panel for easy adjustment.

### Configurable Outputs

Outputs 120 Watts at a variety of typical commercial speaker settings: 50V, 70V, 100V, or 4 Ohm.

### LED Peak Meter

Adjust master volume in tune with the front-panel LED meter to ensure accurate power handling, and to protect any connected speakers.

### 5-Year Limited Warranty

This Episode® Commercial Amplifier has a 5-Year Limited Warranty. This warranty includes parts and labor repairs on all components found to be defective in material or workmanship under normal conditions of use. This warranty shall not apply to products which have been abused, modified or disassembled. Products to be repaired under this warranty must be returned to SnapAV or a designated service center with prior notification and an assigned return authorization number.