# FULGOR

### 30"-36" Full Gas Ranges 600 SERIES

#### mir 48″ (1220) 13" Minimum to Combustible (330) mii 30" (762) To botton of min 18" min 18' (457) (457) min 6″ min 6″ (152) (152) (90 \*Suggested 4-2" (51) max. location of utilities protusion from wall for gas or electrical supply GAS ELECTRIC **◀** в **▶◀** в **▶** 4 3/4" (123)SHADED AREA: OPENING WIDTH A & C в The surface of the entire back wall above the range and below the hood Range 30" 30" (762) 6" (152)

\*Consult local code for exact location requirements. Note: Clearances from non-combustible materials are not part of the ANSI Z21.1 scope and not certified. Clearances to non-combustible materials must conform with local codes or, in the absence of local codes, with the National Fuel Gas Code, ANSI Z223.1/NFPA 54.

must be covered with a noncombustible material.

#### Minimum clearances:

Range 36"

Above cooking surface (above 36" [91.4 cm])

• Sides - 6" (15.2 cm)

• Within 6" (15.2 cm) side clearance, wall cabinets no deeper than 13" (33.0 cm) must be minimum

7" (178)

18" (45.7 cm) above cooking surface

• Wall cabinets directly above product must be a minimum of 48" (122 cm) above cooking surface. • Rear - 0" with 9 " backguard; 0" with non-combustible rear wall.

36" (914)

Below cooking surface (36" [91.4 cm] and below) • Install with zero clearance between adjacent combustible construction below the cooking surface and the back and sides of the appliance



For island installation, maintain 2-1/2 in. minimum from cutout to back edge of countertop and 3 in. minimum from cutout to side edges of countertop (see top view). For island installation, 12" (305) minimum clearance back of range to combustible rear wall above countertop. The island installation is not part of the ANSI Z21.1 scope and not certified.





PACKAGING 30"		lb / inch	Kg / mm
GROSS WEIGHT		322 lb	146 Kg
DIMENSION	W	33"	840
	D	45"3/4	1162
	H	32"1/4	820
PACKAGING 36"		lb /	Kg /
		inch	mm
GROSS WEIGHT		377 lb	171 Kg
GROSS WEIGHT	w		
GROSS WEIGHT	W	377 lb	171 Kg



## Weight & Dimensions