

CLW-SWEX-P

Cameo® Wireless In-Wall Switch, 120V

- > Field-replaceable, engravable buttons
- > Available in all designer colors
- > Robust infiNET EX® communication
- > Models popular Cameo® style
- > Configurable with rocker or 2 buttons
- > Matching aesthetics across entire line
- > Supports remote dimmers and switches (CLW-SLVU-P)
- > Screw-clamp connectors for easy installation
- > Stylish bargraph provides real-time status feedback

The CLW-SWEX-P is a Cameo® wireless in-wall switch which features field-replaceable, engravable buttons. Available in designer colors and configurable with two buttons or in a rocker layout, the CLW-SWEX-P is more versatile than previous generations of in-wall switches. Its streamlined design matches the entire line of Cameo dimmers, switches and keypads, making it a great addition to new or retrofit installations. In addition to its attractive look and feel, infiNET EX® communication technology brings proven reliability to the CLW-SWEX-P.

Field-Replaceable Button Faces

Like their cousin Cameo keypads, the buttons on the CLW-SWEX-P can be swapped in the field, making it easy to change engraving or color after installation. The rocker controller brings a familiar user interface to the Crestron® in-wall switch, while the two-button layout offers clear on/off control.

infiNET EX

Ultra-reliable infiNET EX wireless technology provides steadfast two-way RF communications throughout a residential or commercial structure without the need for physical control wiring. Employing a 2.4 GHz mesh network topology, each infiNET EX device functions as an expander, passing command signals through to every other infiNET EX device within range (approximately 150 feet or 46 meters indoors), ensuring that every command reaches its intended destination without disruption.^[1]

The CLW-SWEX-P communicates with a Crestron control system via an infiNET EX Wireless Gateway (model CEN-RFGW-EX, DIN-AP3MEX, or MC3^[2]). Up to 100 infiNET EX devices, including Cameo Wireless Keypads

and In-Wall Switches^[2], may coexist on a single wireless network, and every device that is added to the network effectively increases the range and stability of the entire network by providing multiple redundant signal paths^[1].

Streamlined Installation

In addition to field replaceable buttons, the CLW-SWEX-P features screw-clamp connectors for simplified wiring while reducing installation time and material costs. So slim, the Cameo line can be installed in standard gang boxes making them the perfect choice for both new and retrofit projects.

Remote Switch

The CLW-SWEX-P supports control of the same lights from more than one location. Easily replace existing dimmers and switches wired in a traditional three- or four-way circuit with on/off control from every location, or design new projects to accommodate remote switches wherever desired. The [CLW-SLVU-P](#) remote dimmer simply connects to the “traveler” wire and switches the load attached to the CLW-SWEX-P.

Custom Programmable Keypad

Because the CLW-SWEX-P is attached to the Crestron network, it can also function as a keypad, sending commands to trigger whole-room or house lighting scenes, or any other function. The two-button layout takes advantage of prime single-gang wall box real estate. Use buttons to control in-room audio or lamps. Press-and-hold and double-tap functionality allows buttons to be used for more than just one function.



Due to differences in monitors, actual colors may vary from colors as they appear onscreen.

CLW-SWEX-P Cameo® Wireless In-Wall Switch, 120V

SPECIFICATIONS

Load Ratings

Incandescent / Tungsten Halogen / Magnetic Ballast: 1000 VA/Watts;
Electronic Ballasts / CFL: 600VA;
Motor: 1/2 HP
Minimum Load: 25 Watts

Power Requirements

120 Volts AC, 60Hz, line power

Controls

Button: Configurable for 1 or 2 single-action pushbuttons, programmable via control system

LED Indicator

Feedback: (1) White LED

Wireless

RF Transceiver: infiNET EX® 2-way RF, 2.4 GHz ISM Channels 11-26 (2400 to 2483.5 MHz), default channel 15; IEEE 802.15.4 compliant

Range (typical): 150 ft (46 m) indoor, 250 ft (76 m) outdoor to nearest mesh network device(s); subject to site-specific conditions and individual device capabilities^[1]

Gateway: Requires an infiNET EX gateway^[2]

Connections

Hot: (1) 14-12 AWG, screw terminal, brass, line power input
Remote: (1) 14-12 AWG, screw terminal, blue, remote
Load: (1) 14-12 AWG, screw terminal, red, load output
Neutral: (1) 14-12 AWG, screw terminal, silver, neutral^[3]
Ground: (1) 18 AWG Class 1 flying lead, green, ground (wire nut included)

Environmental

Temperature: 32° to 104°F (0° to 40°C)
Humidity: 10% to 90% RH (non-condensing)

Enclosure

1-gang mountable in a 3-1/2 inch deep electrical box;
Requires decorator style faceplate (not included)

Dimensions

Height: 4.13 in (105 mm)
Width: 1.75 in (45 mm)
Depth: 1.75 in (45 mm)

Weight

5 oz (142 g)

MODELS & ACCESSORIES

Available Models

CLW-SWEX-P-A-S: Cameo® Wireless In-Wall Switch, 120V, Almond Smooth
CLW-SWEX-P-A-T: Cameo® Wireless In-Wall Switch, 120V, Almond Textured
CLW-SWEX-P-B-S: Cameo® Wireless In-Wall Switch, 120V, Black Smooth
CLW-SWEX-P-B-T: Cameo® Wireless In-Wall Switch, 120V, Black Textured
CLW-SWEX-P-BRN-S: Cameo® Wireless In-Wall Switch, 120V, Brown Smooth
CLW-SWEX-P-DA-S: Cameo® Wireless In-Wall Switch, 120V, Dark Almond Smooth
CLW-SWEX-P-DSK-T: Cameo® Wireless In-Wall Switch, 120V, Dusk Textured
CLW-SWEX-P-GRY-S: Cameo® Wireless In-Wall Switch, 120V, Gray Smooth
CLW-SWEX-P-IVR-S: Cameo® Wireless In-Wall Switch, 120V, Ivory Smooth
CLW-SWEX-P-LAT-T: Cameo® Wireless In-Wall Switch, 120V, Latte Textured
CLW-SWEX-P-W-S: Cameo® Wireless In-Wall Switch, 120V, White Smooth
CLW-SWEX-P-W-T: Cameo® Wireless In-Wall Switch, 120V, White Textured

Included Accessories

CLW-BTN-RKR-A-S: Rocker Engravable Button Cap (blank), Almond, Gloss [Included Quantity for CLW-SWEX-P-A-S: 1]
CLW-BTN-RKR-A-T: Rocker Engravable Button Cap (blank), Almond, Matte [Included Quantity for CLW-SWEX-P-A-T: 1]
CLW-BTN-RKR-B-S: Rocker Engravable Button Cap (blank), Black, Gloss [Included Quantity for CLW-SWEX-P-B-S: 1]
CLW-BTN-RKR-B-T: Rocker Engravable Button Cap (blank), Black, Matte [Included Quantity for CLW-SWEX-P-B-T: 1]
CLW-BTN-RKR-BRN-S: Rocker Engravable Button Cap (blank), Brown, Gloss [Included Quantity for CLW-SWEX-P-BRN-S: 1]
CLW-BTN-RKR-DA-S: Rocker Engravable Button Cap (blank), Dark Almond, Gloss [Included Quantity for CLW-SWEX-P-DA-S: 1]
CLW-BTN-RKR-DSK-T: Rocker Engravable Button Cap (blank), Dusk, Matte [Included Quantity for CLW-SWEX-P-DSK-T: 1]
CLW-BTN-RKR-GRY-S: Rocker Engravable Button Cap (blank), Gray, Gloss [Included Quantity for CLW-SWEX-P-GRY-S: 1]
CLW-BTN-RKR-IVR-S: Rocker Engravable Button Cap (blank), Ivory, Gloss [Included Quantity for CLW-SWEX-P-IVR-S: 1]
CLW-BTN-RKR-LAT-T: Rocker Engravable Button Cap (blank), Latte, Matte [Included Quantity for CLW-SWEX-P-LAT-T: 1]
CLW-BTN-RKR-W-S: Rocker Engravable Button Cap (blank), White, Gloss [Included Quantity for CLW-SWEX-P-W-S: 1]
CLW-BTN-RKR-W-T: Rocker Engravable Button Cap (blank), White, Matte [Included Quantity for CLW-SWEX-P-W-T: 1]

Available Accessories

CEN-RFGW-EX: infiNET EX® Wireless Gateway
CEN-RFGW-EX-PWE: infiNET EX® Wireless Gateway w/PoE Injector
MC3: 3-Series Control System® w/infiNET EX®

CLW-SWEX-P Cameo® Wireless In-Wall Switch, 120V

DIN-AP3MEX: DIN Rail 3-Series® Automation Processor w/infiNET EX®

CLW-EXPEX-GD-W-T: infiNET EX® Wireless Expander, Ground Pin Down, White Textured

GLA-EXPEX: Crestron Green Light® Wireless Expander for infiNET EX® Networks

CLW-BTN-LG-A-S: Large Engravable Button Cap, Almond, Gloss

CLW-BTN-LG-A-T: Large Engravable Button Cap, Almond, Matte

CLW-BTN-LG-B-S: Large Engravable Button Cap, Black, Gloss

CLW-BTN-LG-B-T: Large Engravable Button Cap, Black, Matte

CLW-BTN-LG-BRN-S: Large Engravable Button Cap, Brown, Gloss

CLW-BTN-LG-DA-S: Large Engravable Button Cap, Dark Almond, Gloss

CLW-BTN-LG-DSK-T: Large Engravable Button Cap, Dusk, Matte

CLW-BTN-LG-GRY-S: Large Engravable Button Cap, Gray, Gloss

CLW-BTN-LG-IVR-S: Large Engravable Button Cap, Ivory, Gloss

CLW-BTN-LG-LAT-T: Large Engravable Button Cap, Latte, Matte

CLW-BTN-LG-W-S: Large Engravable Button Cap, White, Gloss

CLW-BTN-LG-W-T: Large Engravable Button Cap, White, Matte

CLW-BTN-RKR-A-S: Rocker Engravable Button Cap, Almond, Gloss

CLW-BTN-RKR-A-T: Rocker Engravable Button Cap, Almond, Matte

CLW-BTN-RKR-B-S: Rocker Engravable Button Cap, Black, Gloss

CLW-BTN-RKR-B-T: Rocker Engravable Button Cap, Black, Matte

CLW-BTN-RKR-BRN-S: Rocker Engravable Button Cap, Brown, Gloss

CLW-BTN-RKR-DA-S: Rocker Engravable Button Cap, Dark Almond, Gloss

CLW-BTN-RKR-DSK-T: Rocker Engravable Button Cap, Dusk, Matte

CLW-BTN-RKR-GRY-S: Rocker Engravable Button Cap, Gray, Gloss

CLW-BTN-RKR-IVR-S: Rocker Engravable Button Cap, Ivory, Gloss

CLW-BTN-RKR-LAT-T: Rocker Engravable Button Cap, Latte, Matte

CLW-BTN-RKR-W-S: Rocker Engravable Button Cap, White, Gloss

CLW-BTN-RKR-W-T: Rocker Engravable Button Cap, White, Matte

CLW-SLVU-P-A-S: Cameo® In-Wall Remote Dimmer, 120V, Almond Smooth

CLW-SLVU-P-A-T: Cameo® In-Wall Remote Dimmer, 120V, Almond Textured

CLW-SLVU-P-B-S: Cameo® In-Wall Remote Dimmer, 120V, Black Smooth

CLW-SLVU-P-B-T: Cameo® In-Wall Remote Dimmer, 120V, Black Textured

CLW-SLVU-P-BRN-S: Cameo® In-Wall Remote Dimmer, 120V, Brown Smooth

CLW-SLVU-P-DA-S: Cameo® In-Wall Remote Dimmer, 120V, Dark Almond Smooth

CLW-SLVU-P-DSK-T: Cameo® In-Wall Remote Dimmer, 120V, Dusk Textured

CLW-SLVU-P-GRY-S: Cameo® In-Wall Remote Dimmer, 120V, Gray Smooth

CLW-SLVU-P-IVR-S: Cameo® In-Wall Remote Dimmer, 120V, Ivory Smooth

CLW-SLVU-P-LAT-T: Cameo® In-Wall Remote Dimmer, 120V, Latte Textured

CLW-SLVU-P-W-S: Cameo® In-Wall Remote Dimmer, 120V, White Smooth

CLW-SLVU-P-W-T: Cameo® In-Wall Remote Dimmer, 120V, White Textured

Notes:

1. Any infiNET EX device that provides expander functionality will effectively extend the range of the wireless network beyond the initial range of the gateway. Battery-powered infiNET EX devices do not provide expander functionality. A dedicated infiNET EX Wireless Expander, model CLW-EXPEX or GLA-EXPEX is also available.
2. Item(s) sold separately.
3. A neutral wire is required for normal operation. Refer to the manual for alternate wiring configurations.

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/salesreps or by calling 800-237-2041.

The specific patents that cover Crestron products are listed online at: patents.crestron.com.

Crestron, the Crestron logo, 3-Series, 3-Series Control System, Cameo, Crestron Green Light, and infiNET EX are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography. Specifications are subject to change without notice. ©2014 Crestron Electronics, Inc.

CLW-SWEX-P Cameo® Wireless In-Wall Switch, 120V

CAD DRAWINGS

