

## Be exact. The original soundbar.

Leon's Horizon™ Series speakers are hand-crafted and built-to-order to match the **exact width and finish of any flat-panel display**. Combining left, center and right channels all in one sleek cabinet, the Horizon™ Series provides picture perfect sound for Living Space home theater systems and everyday TV viewing. The Horizon™ 414 Series, one of Leon's most popular product lines, offers some of the best and most accessible world-class audio products on the market. Each Horizon 414 speaker features high-performance woofers and cloth-dome tweeters, with several available upgrades, creating a true high-fidelity system with brilliant reproduction of vocals, music and movie sound effects. Leon's Horizon 414 Series offers one of the most dynamic audio solutions for residential and commercial environments.

### Custom built to match the **exact width and finish of any display**

Easily mounts to articulating TVs with Leon's exclusive brackets

Slim 3.25" deep design ensures compatibility with flat-screen TVs

Angled baffles available for overmount or high placement applications

Solid MDF construction, meticulously crafted by hand

Available as LCR, LR or Center channels

**Recommended Pairings:** Axis AX-V6, Detail Ds114-X-A, Vault v114i-X-A, Timbre Ti400-X-A, Aaros A10-UT



▲ Hz414-LCR shown above without grill

<p>▼ <b>Hz414</b></p>	<table> <tr> <td>Components</td><td>4" woofers; 1" cloth-dome tweeters</td></tr> <tr> <td>Configuration(s)</td><td>Hz414-LCR, Hz414-LR; Hz414-C</td></tr> <tr> <td>Dimensions</td><td>5.75" (h) x 3.25" (d) x exact width of TV</td></tr> <tr> <td>Freq. Resp.</td><td>Left/Center/Right: 90-20kHz</td></tr> <tr> <td>Sensitivity</td><td>Left/Center/Right: 88dB@2.83V/1m</td></tr> <tr> <td>Impedance</td><td>Left/Right: 6Ω; Center: 8Ω</td></tr> <tr> <td>Rec. Power</td><td>Left/Center/Right: 50-150W</td></tr> <tr> <td>Max. Output</td><td>Left/Center/Right: 103 dB; 109 dB peak</td></tr> <tr> <td>Weight</td><td>12-30 lbs.</td></tr> <tr> <td>Mounting</td><td>HzUMB, HzOMB, HzMMB, HzTTS</td></tr> </table>	Components	4" woofers; 1" cloth-dome tweeters	Configuration(s)	Hz414-LCR, Hz414-LR; Hz414-C	Dimensions	5.75" (h) x 3.25" (d) x exact width of TV	Freq. Resp.	Left/Center/Right: 90-20kHz	Sensitivity	Left/Center/Right: 88dB@2.83V/1m	Impedance	Left/Right: 6Ω; Center: 8Ω	Rec. Power	Left/Center/Right: 50-150W	Max. Output	Left/Center/Right: 103 dB; 109 dB peak	Weight	12-30 lbs.	Mounting	HzUMB, HzOMB, HzMMB, HzTTS
Components	4" woofers; 1" cloth-dome tweeters																				
Configuration(s)	Hz414-LCR, Hz414-LR; Hz414-C																				
Dimensions	5.75" (h) x 3.25" (d) x exact width of TV																				
Freq. Resp.	Left/Center/Right: 90-20kHz																				
Sensitivity	Left/Center/Right: 88dB@2.83V/1m																				
Impedance	Left/Right: 6Ω; Center: 8Ω																				
Rec. Power	Left/Center/Right: 50-150W																				
Max. Output	Left/Center/Right: 103 dB; 109 dB peak																				
Weight	12-30 lbs.																				
Mounting	HzUMB, HzOMB, HzMMB, HzTTS																				
<p>▼ <b>Hz414-X-A</b></p>	<table> <tr> <td>Components</td><td>4" woofers; 1" audiophile tweeters</td></tr> <tr> <td>Configuration(s)</td><td>Hz414-LCR-X-A, Hz414-LR-X-A; Hz414-C-X-A</td></tr> <tr> <td>Dimensions</td><td>5.75" (h) x 3.25" (d) x exact width of TV</td></tr> <tr> <td>Freq. Resp.</td><td>Left/Center/Right: 90-22kHz</td></tr> <tr> <td>Sensitivity</td><td>Left/Center/Right: 88dB@2.83V/1m</td></tr> <tr> <td>Impedance</td><td>Left/Center/Right: 8Ω</td></tr> <tr> <td>Rec. Power</td><td>Left/Center/Right: 50-200W</td></tr> <tr> <td>Max. Output</td><td>Left/Center/Right: 104 dB; 110 dB peak</td></tr> <tr> <td>Weight</td><td>12-30 lbs.</td></tr> <tr> <td>Mounting</td><td>HzUMB, HzOMB, HzMMB, HzTTS</td></tr> </table>	Components	4" woofers; 1" audiophile tweeters	Configuration(s)	Hz414-LCR-X-A, Hz414-LR-X-A; Hz414-C-X-A	Dimensions	5.75" (h) x 3.25" (d) x exact width of TV	Freq. Resp.	Left/Center/Right: 90-22kHz	Sensitivity	Left/Center/Right: 88dB@2.83V/1m	Impedance	Left/Center/Right: 8Ω	Rec. Power	Left/Center/Right: 50-200W	Max. Output	Left/Center/Right: 104 dB; 110 dB peak	Weight	12-30 lbs.	Mounting	HzUMB, HzOMB, HzMMB, HzTTS
Components	4" woofers; 1" audiophile tweeters																				
Configuration(s)	Hz414-LCR-X-A, Hz414-LR-X-A; Hz414-C-X-A																				
Dimensions	5.75" (h) x 3.25" (d) x exact width of TV																				
Freq. Resp.	Left/Center/Right: 90-22kHz																				
Sensitivity	Left/Center/Right: 88dB@2.83V/1m																				
Impedance	Left/Center/Right: 8Ω																				
Rec. Power	Left/Center/Right: 50-200W																				
Max. Output	Left/Center/Right: 104 dB; 110 dB peak																				
Weight	12-30 lbs.																				
Mounting	HzUMB, HzOMB, HzMMB, HzTTS																				

\*LCR speakers smaller than 48" wide can only accommodate (4) 4" midrange woofers