

gKP7 7 Button Single Gang Keypad



ORDER NO. gKP7



gKP7



The Next Step in Home Control

It's not too big, and definitely unassuming, but the ELAN gKP7 puts simple to use power where you need it. The gKP7 provides the end-user with valuable back-lit control that always works, never runs out of batteries, and does what it says at a price that fits any budget.

The gKP7 was designed to aesthetically match the ELAN Lighting 7 button keypads and offers five completely programmable buttons and two raise/lower buttons with flexible functionality as well. Depending on your needs the five function buttons may be mix and match programmed using g! Configurator to be used as a media favorite preset, to execute a lighting scene, act as zone/system off, or to execute an Event Mapper automated event while the bottom two raise/lower buttons may be configured to either operate zone volume or lower and raise a lighting scene or shade group. As with most things complex when using the g! Configurator interface personalization is simple and efficient.

As a media interface the gKP7 dedicates to one zone and allows the end-user to conveniently store & recall; stations from any g! supported two way tuner, playlists from an ELAN g1 MP3 player, channels & playlists from premium streaming content devices (Autonomic, LMS & Sonos), as well as access & initiate playback from legacy sources like CD players. All the end-user has to do is use a touch panel interface to access the desired media and then press and hold the Favorite button to store. Recalling is as simple as pressing the Favorite button.

For lighting you may assign a KP7 button toggle any system lighting scene or dimmer. Pressing the button executes the lighting scene and lights the buttons back-lighting. A second press turns the scene off as well as the button LED.

Event Mapper puts the power of automation at your fingertip as gKP7 buttons may be programmed to do virtually anything through programming by an ELAN certified technician. Want to turn off the lights, shut the blinds, and set back the thermostat? No problem. The Event Mapper even allows you to control the LED state for accurate feedback.

The lower two buttons may be programmed to either lower and raise the volume in the audio zone, the lighting of the last selected scene, or to perform custom Event Map actions.

The gKP7 ships with white buttons and bezel and includes 10 extra buttons for your convenience. Light almond (gKP7BK-LA) and black (gKP7BK-B) color change kits are available and include the bezel and all sixteen buttons included with the white gKP7.

Includes 16 pre-engraved buttons. Custom engraving available.



Comes in white with optional black or light almond bezel kit

gKP7 7 Button Single Gang Keypad

ORDER NO. gKP7

FEATURES

- 7-button backlit keypad
- Defaulted to four favorite channels plus volume up
- PoE for single wire hookup
- Programmable through gConfigurator for five different button actions.
- Custom engraveable buttons
- Gangable with any 1g device
- Comes in white with optional black or light almond bezel kit

Note: Decorator trim plate not included

SPECIFICATIONS	
Dimensions	4.12" x 1.75" x 1.24"
Mounting Depth	1.75"
Button type	<ul style="list-style-type: none"> Contact type buttons 5 individually capped 2 shared for rocker capping 5 individually controlled white LEDs for backlighting 2 shared control white LEDs for backlighting 1/100/1000 Ethernet
Connections	LAN/ PoE RJ-45
Power Requirements	PoE (Power over Ethernet) IEEE 802.3at, 1.3w maximum draw (@48 V= 270mA max
Included in box	(1) gKP7 single gang keypad with white Favorite 1-4, Off and V / \ buttons installed (2) Mounting screws (1) Quick Install Guide (1) Alternate button pack
Available Separately	gKP7BK-LA – Light Almond color change kit gKP7BK-B – Black color change kit Custom Engraved Buttons visit www.elanhomesystems.com/engraving

BUTTONS INCLUDED WITH KEYPAD

Favorite 1	Home Mode	Mute
Favorite 2	Stay Mode	☺
Favorite 3	Away Mode	☁
Favorite 4	Shade ☺	☀
Off	Shade ☺	
☺ Vol ☺	☺ ☺	



gKP7BK-B Button Kit